FOCUSED ON GENERATORS ONLY

Power Generator FDG 365 S2

MAIN FEATURES

Highest quality and reliability.	Wide range of standard and optional equipment.
ComAp IL-NT AMF25 controller.	Engine heater – ready to load just after start.
Ready to control MAINS – GENERATOR transfer switch.	Drip tray,
Configured for both manual and automatic mode (MRS + AMF).	Anticorrosion coating: frame - Zr, canopy – Zr, Al-Zn.
Wide range of remote communications options.	Brushless alternator.
Schneider NSX type GCB.	

The presented image is for illustration purpose only.

GENERAL DATA

Code	F.0365.S2A.G
Standby power E.S.P. [kVA] / [kW]	400,0 / 320,0
Prime power P.R.P. [kVA] / [kW]	365,0 / 292,0
Prime current P.R.P [A]	527,0
Frequency [Hz]	50
Voltage [V]	400
Exhaust emission	Stage II
Fuel type	Diesel (EN 590)
Fuel consumption - 50% load [l/h]	38,2
- 75% load [l/h]	56,6
- 100% load [l/h]	76,1
- 110% load [l/h]	84,4
Standard fuel tank capacity [l]	990
Autonomy with 100% load [h]	12
Engine control voltage [V]	24
Weight without fuel [kg]	~4650
Dimensions L x W x H [mm]	4560 x 1961 x 2521
Guaranteed noise power Lwa [dBA]	~97
Acoustic pressure Lpa (7m) [dBA]	~68

Nominal power P.R.P:
Prime power available in variable load application in accordance with ISO 8528, 10% overload capacity is available for a period of 1 hour within a 12-hour period of operation. Average power consumption should not exceed 70% PRP for each 24-hour period of operation.

Stand-by power E.S.P.:
Emergency standby power rating is applicable for supplying emergency power for the duration of a utility power interruption. No overload allowed, limited to 200h of operation per year. Max mean load factor of 70% of rated power over 24-hour period of operation.

Remark:
Ratings represent the genset performance capabilities to standard conditions specified in ISO 8528-1

Norms and directives:

- Machinery directive 2006/42/EC
- Low voltage directive 2014/35/EC
- EC directive 2014/30/EC
- Noise directive 2000/14/EC
- Emission directive 97/68/EC
- ISO 8528-1:2005, ISO 8528-5:2013
- ISO 8528-13:2016
- EN 60204-1

www.fogo.pl

FOGO Sp. z o.o.
ul. Święciechowska 36, Wilkowice
64-115 Święciechowa

tel. +48 65 534 11 80
fax +48 65 534 11 81
generators@fogo.pl

FOCUSED ON GENERATORS ONLY

Power Generator FDG 365 S2

STANDARD CONTROLLER

- Controller type: AMF 25
- Easy to operate, intuitive graphical interface
- Real time clock with battery supply
- AMF function available
- Flexible event based history with up to 119 events
- 3 Phase generator current measurement
- Generator and Mains phase voltage measurement
- Active/reactive power measurement
- Active and reactive energy counter
- Running hours counter
- Battery charging alternator circuit connection
- Fuel level measurement
- Generator protection (over/under frequency, voltage, overcurrent)
- Communication with ECU supporting CAN J1939 standard
- Communication interface RS 485 and RS 232 supporting Modbus RTU (IL-NT RS232-485 module required)
- GSM modem / wireless internet (IL-NT GPRS module required)
- Internet/Ethernet communication (IB-Lite module required)
- InteliMonitor software for single gen-set view
- WebSupervisor software for Android mobile devices or PC's for fleet management
- Active SMS or e-mail (IL-NT GPRS or IB-Lite module required)

ENGINE

Brand	Scania
Type	DC13 073A 02-21
Made in	Sweden
Engine power [kW]	320,0
Emission standard*	stage II
Rotation per minute [rpm]	1500
Engine governor	electonic
Governor class**	G3
Displacement [l]	12,7
No of cylinder	6
Fuel system	unit injectors, PDE
Electrical system [V]	24
Cooling system capacity [l]	38,0
Oil pan capacity [l]	36,0
Fuel type	Diesel (EN 590)

ALTERNATOR

Nominal Voltage [V]	400
Nominal power factor (cos phi)	0,8
Ambient temperature, altitude	40 ºC, 1000m a.m.s.l
Nominal Power [kVA]	365,0
IP protection	IP 23
No of bearing	single bearing
Coupling	direct
Technology	brushless
Short circuit maintaining capacity	270% 10s
Efficiency [%]	93,4
Insulation class	H
Total harmonic content THD [%]	2,5
Reactance Xd'' [%]	11,6
Voltage regulator type	DVR, digital
Voltage measurement	3 phases
Voltage accuracy [%]	+/- 0,25
AVR supply system	auxiliary winding
AVR supply optional	PMG
Made in	EU

* According directive 97/68/EC non road mobile machinery engine emission.
** According ISO 8528-5:2013

www.fogo.pl

FOGO Sp. z o.o.
ul. Święciechowska 36, Wilkowice
64-115 Święciechowa

tel. +48 65 534 11 80
fax +48 65 534 11 81
generators@fogo.pl

FOCUSED ON GENERATORS ONLY

Power Generator FDG 365 S2

STANDARD EQUIPMENT	
Scania DC13 073A 02-21 engine	✓
Electronic engine speed governor	✓
Oil low pressure switch	✓
Oil pressure sensor	✓
Engine high temperature switch	✓
Engine high temperature sensor	✓
Engine preheating with thermostat	✓
Engine oil Titan Cargo 15W40	✓
Oil draining hand pump	✓
Fuel filter with water separator	✓
Coolant Fuchs Maintain Fricofin LL-35	✓
Coolant inlet outside of the canopy	✓
Starting batteries 2x180Ah	✓
Battery charger	✓
GCB Schneider NSX 630 3P + Mic.2.3	✓
GCB shunt release coil	✓
Controller ComAp IL-NT-AMF25	✓
Controller switch	✓
Acoustic alarm	✓
Emergency stop button	✓
Silenced canopy made with Al.-Zn.	✓
Standard color RAL 7032	✓
Fuel tank installed in drip tray	✓
Welded frame with fuel tank	✓
Fuel inlet inside, protected by canopy locked doors	✓
Fuel level measurement	✓
Exhaust compensator and silencer	✓
Engine and alternator vibro isolators	✓
Transportation brackets	✓

OPTIONAL EQUIPMENT	
Battery disconnection switch	✓
GCB 4P Schneider NSX Micrologic 2.3	✓
Power Lock type power output	✓
Power socket box	✓
Transfer switch controlled by generator controller	✓
Transfer switch with ATS controller	✓
GPRS communication card	✓
Ethernet card	✓
RS 485, RS 232 card	✓
Remote display	✓
Drip space level sensor	✓
External fuel tank 1 000 – 10 000 l	✓
3-way valve for external fuel tank connection	✓
Fuel tank filling pump and shut-off valve	✓
Non-standard canopy color (RAL palette)	✓

FOGO Sp. z o.o.
ul. Święciechowska 36, Wilkowice
64-115 Święciechowa

tel. +48 65 534 11 80
fax +48 65 534 11 81
generators@fogo.pl

INSTALLATION GUIDELINES

Power terminal	GCB terminal
Recommended cable for up to 30m power cable way	Flexible 2x5x120 mm^2
Recommended cable for do 30m generator heater supply	Flexible 3x2,5 mm^2
*For additional cable connection with FOGO ATS see ATS wiring diagram	
Exhaust pipe min diameter (max. 7 m, 4 bends)	133 mm
Exhaust pipe min diameter (max. 15 m, 4 bends)	

MAINTENANCE GUIDELINES

Fuel filters replacement	500 h / 1 year
Oil replacement	After first 100h, then every 500 h / 1 year
Oil filters replacement	After first 100h, then every 500 h / 1 year
Coolant replacement	1000 h / 2 years
Battery replacement	2 years
Electrical installation supervising	According to local requirements, at least once per year

WARRANTY

Continuous work generators	12 months up to 1000 working hours

www.fogo.pl

FOGO Sp. z o.o.
ul. Święciechowska 36, Wilkowice
64-115 Święciechowa

tel. +48 65 534 11 80
fax +48 65 534 11 81
generators@fogo.pl