



# Power generator

## FV 10001 CRA

### Characteristic

- Voltage stabilization  $\pm 2\%$
- Low level of THD  $< 4\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP 23
- Full single phase power output socket 63 Amps
- Autonomy (at 75 % load) 11 h
- Cicha praca - Hałas Lwa 92 dB(A)
- Ready for manual and automatic operation

### Technical parameters

<b>Frequency</b>	<b>50 Hz</b>
<b>Voltage</b>	<b>230 V</b>
<b>Nominal power</b>	<b>8,6 kW</b>
<b>Maksimum power</b>	<b>9,5 kW</b>
Engine	Vanguard
Model	3564
Displacement	570 cm <sup>3</sup>
Cooling	Air
Cylinder	2
Stroke	4
Oil volume	1,7 L
Starting system	Electric starter
Fuel	Petrol
Fuel tank	50 L
Consumption (load 75%)	4,5 L / h
Noise Lwa	92 dB(A)
Weight	220 kg
Length	1100 mm
Width	600 mm
Height	830 mm

### Standard equipment

- AVR
- Socket 230 V 16 A
- Socket 230 V 32 A
- Socket 230 V 63 A
- Overload protection
- Oil pressure sensor
- Silencer with exhaust adapter
- Battery
- Connection for ATS panel
- Hourmeter

### Optional and service equipment

- Exhaust hose
- Service kit (air filter, spark plugs, engine oil)

### Norms and Directives

- **2000/14/WE**  
Noise directive 2005/88/WE
- **2006/42/WE**  
Machinery directive
- **2014/35/WE**  
Low voltage directive
- **2014/30/WE**  
EC directive